

## ► Základní nastavení ZTE H6645P pro přístup k internetu

Zapojíme router ZTE H6645P a přes LAN1 port připojíme notebook nebo stolní počítač. Alternativou je připojení přes WiFi, název sítě a heslo je na spodní straně routeru.

Do internetového prohlížeče (např. Microsoft Edge, Google chrome...) zadáme adresu **192.168.1.1**

Přihlásíme se od routeru:

Username: **admin**

Password: **Haikui\_V2**

▲ Nezabezpečeno | 192.168.1.1

**ZTE**

Home Topology Internet Local Network VoIP Management & Diagnosis

Welcome to H6645P V2. Please login.

Username

Password

Login


©2008-2022 ZTE Corporation. All rights reserved | H6645P V2 V2.1.0P1N1\_TY


Po prvním přihlášení je možné nastavit **nové heslo**.


V případě, že nechcete heslo změnit, zvolte CANCEL.

**ZTE**



 **Welcome to H6645P V2**

 Note: For security, please modify the initial password.

 A strong password should match these rules:

1. It should have at least 8 characters.
2. It should be composed of digits, alphabet and special symbols.
3. It should not have context relationship with the username, such as the same or inverse.

Username

New Password

Confirmed Password

V horní záložce zvolíme INTERNET a v levém menu zvolíme WAN

The screenshot displays the ZTE router's web management interface. At the top, the ZTE logo is on the left, and the current time '1970-01-01T00:18' and user 'admin' with a 'Logout' link are on the right. A navigation bar contains 'Home', 'Topology', 'Internet' (highlighted with a red box), 'Local Network', 'VoIP', and 'Management & Diagnosis'. On the left, a sidebar menu lists various settings, with 'WAN' highlighted in a red box. The main content area is titled 'Page Information' and 'Ethernet Connection'. The 'Ethernet Connection' section shows a 'New Item' configuration form with the following fields: 'Connection Name' (text input), 'Type' (dropdown menu set to 'Routing'), 'Service List' (checkboxes for 'INTERNET', 'TR069', 'VoIP', and 'IPTV', all checked), 'MTU' (text input set to '1492'), 'Link Type' (dropdown menu set to 'PPP'), and 'PPP Transfer Type' (dropdown menu set to 'PPPoE'). Below these are 'PPP' settings: 'Username' and 'Password' (text inputs), 'IP Version' (dropdown menu set to 'IPv4'), and 'VLAN' (radio buttons for 'On' and 'Off', with 'Off' selected). 'Apply' and 'Cancel' buttons are at the bottom right. A '+ Create New Item' button is at the bottom left.


Novou položku WAN vyplníme následovně:

- 1) Connection Name: **WAN\_Internet**
- 2) PPP sekce se vyplní dle poskytovatele (např. Username **CETIN**, Password **CETIN**)
- 3) VLAN zakliknout **on**
- 4) VLAN ID doplnit hodnotu **848**
- 5) Potvrdíme tlačítkem Apply


## Page Information

This page provides the function of Ethernet connection parameter(s) configuration.

### ▼ Ethernet Connection

▼ New Item Detail 

Connection Name	<input type="text" value="WAN_Internet"/>
Type	<input type="text" value="Routing"/>
Service List	<input checked="" type="checkbox"/> INTERNET <input checked="" type="checkbox"/> TR069 <input checked="" type="checkbox"/> VoIP <input type="checkbox"/> IPTV
MTU	<input type="text" value="1492"/>
Link Type	<input type="text" value="PPP"/>
PPP Transfer Type	<input type="text" value="PPPoE"/>
<b>PPP</b>	
Username	<input type="text" value="CETIN"/>
Password	<input type="password" value="....."/>
IP Version	<input type="text" value="IPv4"/>
VLAN	<input checked="" type="radio"/> On <input type="radio"/> Off
VLAN ID	<input type="text" value="848"/>

 Create New Item

Následně přejděte v menu na položku **Port Binding**:

- 1) Rozklikněte **WAN\_Internet**
- 2) Klikněte na položku **All On**
- 3) Potvrďte tlačítkem **Apply**

The screenshot shows the ZTE router's web management interface. At the top, there is a navigation bar with tabs for Home, Topology, Internet, Local Network, VoIP, and Management & Diagnosis. The 'Internet' tab is selected. On the left side, there is a sidebar menu with various configuration options, and 'Port Binding' is highlighted with a red box. The main content area is titled 'Page Information' and 'Port Binding'. Under 'Port Binding', there is a tree view with 'Route\_3G' expanded to show 'WAN\_Internet', which is also highlighted with a red box. Below this, there is a list of checkboxes for various network services, all of which are checked. At the bottom of this list, there is an 'All On' button, which is highlighted with a red box, and an 'All Off' button. To the right of these buttons are 'Apply' and 'Cancel' buttons. The footer of the page contains the copyright information: '©2008-2022 ZTE Corporation. All rights reserved | H6645P V2 V2.1.0P1N1\_TY'.